


Especificaciones técnicas

SWITCH 812/822/642



Audio Switch

Entradas stereo: SWITCH 812 8

SWITCH 822 8

SWITCH 642 6

Salidas stereo: SWITCH 812 1

SWITCH 822 2

SWITCH 642 4

Diafonía: 120dB @ 100KHz @ 600ohm

Separación I / D: 120dB @ 100KHz @ 600ohm

Ruido: 120dB 20Hz 20KHz @ 600ohm

Entradas/ Salidas: Balanceadas

Microprocesadores: SWITCH 812 1

SWITCH 822 2

SWITCH 642 4

Relé: SWITCH 812 16

SWITCH 822 32

SWITCH 642 48

Alimentación: 110 / 220VCA 40% / +20%,

50 / 60Hz, 30VA



Bermúdez 1231 - Capital Federal - CP 1407 - Buenos Aires - Argentina

Tel: (5411) 4567-3727 - Sitios Web: www.adasnet.com www.veas.tv www.dbdaudio.com - Email: ventas@age.com.ar